



## frequently asked questions

---

### NETWORK QUAD – DEMO MODE

---

#### **“How do I activate/disable the Demonstration Mode”**

Dependent upon the age of the Network Quad, there are two possible ways to enable the demo mode:

##### **Procedure 1 (Older Units)**

1. Press the Timer key.
2. Press the Setup key to display the current mode (T=Master Unit, R=Repeater, D=Demo).
3. Press the Enter key if the mode needs to be changed.
4. Use the Up/Down keys to change mode.
5. Press Enter to store the new mode into memory.
6. Press Timer to complete the change.

##### **Procedure 2 (Newer Units)**

1. Press and hold the Lights and Enter keys together for five seconds to access the diagnostic mode.
2. Using the Up/Down keys, scroll through the various options until Demo is shown.
3. Press Enter
4. Using the Up/Down keys, toggle between On/Off
5. Press Enter to store the setting into memory.
6. Use the Up/Down keys to scroll through to Exit.
7. Press Enter.

--Ends--